



EASY POWER XL/XXL E



La migliore risposta a tutte le esigenze
The best answer to all your requirements

SETTORI DI UTILIZZO



SECTOR OF USE









HPP EVR



HPP EFVR



- Robusto telaio composto da tubolari verniciati con trattamenti anticorrosivi
- Impugnature ergonomiche per agevolare la manovrabilità
- Pannelli di rivestimento in acciaio inox AISI 304
- Pompa di rilancio per aumentare la pressione dell'acqua in aspirazione pompa, con serbatoio 65 lt in acciaio inox
- Pratici alloggiamenti per pistola e lancia
- 2 ruote piene \varnothing 400 con asse in acciaio e cuscinetti a sfere + 2 ruote girevoli con freno
- Motore asincrono trifase 30-37 kW ad alta efficienza IE3
- Giunto elastico di accoppiamento motore-pompa
- Quadro di avviamento e comando industriale in bassa tensione (24V) con avviamento stella-triangolo e 10 metri di cavo alimentazione
- Interruttore con relè termico per la protezione del motore
- Interruttore generale, pulsanti di accensione e spegnimento, stop di emergenza
- Contatore
- Sturdy painted tubular frame with anti-corrosion treatment
- Ergonomic grips for easier manoeuvrability
- AISI 304 stainless-steel coated panels
- Booster pump to increase water pressure at pump inlet, with 65 lt stainless steel water tank
- Practical housings for gun and lance
- 2 x \varnothing 400 solid wheels with steel axle and ball bearings + 2 castor wheels with brake
- Asynchronous three-phase 30-37 kW high-efficiency IE3 motor
- Flexible motor-pump coupling joint
- Industrial low-voltage (24V) power and control panel with star-delta starter and 10 metres of power cable
- Safety switch with thermal magnetic relay for motor protection
- Main switch, start/stop buttons, emergency stop
- Hour counter

Modello Model	Pompa Pump	RPM								
			A	Ph-V-Hz			HP	kW		
EASY POWER XL E 20/800	HPP EVR	1450 1750	63	3-400-50	20	800	40,0	30,0	450	145 x 90 x 105
EASY POWER XL E 15/1000	HPP EVR				15	1000				
EASY POWER XXL E 19/1000	HPP EVR	1450 1750	80	3-440-60	19	1000	50,0	37,0	670	
EASY POWER XXL E 15/1250	HPP EFVR				15	1250				
EASY POWER XXL E 13/1500	HPP EFVR				13	1500				